

# AS/400: Работа с магнитной лентой

⚠ Примеры приведены для лент типа SLR60.

[Здесь](#) дано подробное описание лент SLR.

## Подготовка ленты

Команда: GO TAPE, пункт 2 (Initialize a tape ), device: TAP01, density \*SLR60

или команда:

```
INZTAP DEV(TAP01) NEWVOL(TAPE01) CHECK(*NO) DENSITY(*SLR60)
```

Инициализировать ленту (INZTAP)

Введите варианты, нажмите Enter.

Устройство . . . . .	DEV	>	TAP01
Новый идентификатор тома . . . . .	NEWVOL	>	TAPE01
Идентификатор нового владельца	NEWOWNID		*BLANK
Идентификатор тома . . . . .	VOL		*MOUNTED
Проверка на активные файлы . . . . .	CHECK		*NO
Плотность записи на ленту . . . . .	DENSITY	>	*SLR60
Код . . . . .	CODE		*EBCDIC
Завершение работы с лентой . . . . .	ENDOPT		*REWIND
Очистить . . . . .	CLEAR		*NO

Конец

F3=Выход F4=Приглашение F5=Обновить F12=Отмена F13=Работа с меню

F24=Доп.клав.

После успешной инициализации будет выдано следующее сообщение:

```
Том TAPE01 подготовлен к операции с ИД владельца *BLANK.
```

## Показать информацию о ленте

```
DSPTAP DEV(TAP01)
```

## Статистика качества лент

```
PRTERLOG TYPE(*VOLSTAT) VOLTYPE(6384)
```

## Работа со списком лент

- Запуск [SST](#): STRSST
- Ввод имени и пароля пользователя для входа в SST
- Выбор 1. Start a service tool« from the «System Service Tools (SST)
- Выбор 1. Product activity log

- Выбор 4. Work with removable media lifetime statistics

## Состояние магнитных лент

Команда:

GO SERVICE

QSDMAIN                    ELECTRONIC SERVICE AGENT MAIN MENU

SELECT ONE OF THE FOLLOWING:

1. CHANGE SERVICE AGENT SETTINGS
2. SEND A SERVICE AGENT TEST PROBLEM
3. INVENTORY COLLECTION MENU
4. WORK WITH THE SERVICE AGENT THRESHOLD TABLE
5. DISPLAY SOFTWARE RESOURCES
  
7. CUSTOMER REPORTS MENU

SUBSYSTEM TASKS

8. END SERVICE AGENT SUBSYSTEM
9. START SERVICE AGENT SUBSYSTEM
10. WORK WITH SERVICE AGENT SUBSYSTEM

PROBLEM DETERMINATION

11. CHANGE SERVICE AGENT JOB LOGGING

More...

F1=Help    F3=Exit    F12=Cancel  
(C) COPYRIGHT IBM CORP. 2002, 2002.

Пункт: 7. CUSTOMER REPORTS MENU

QSDCRPT                    Electronic Service Agent Customer Reports Menu

Select one of the following reports:

1. Media Analysis Report
2. Product Activity Log Processing Summary
3. Problem Log Processing Summary
4. Electronic Service Agent PTF Downloads

Bottom

F1=Help    F3=Exit    F12=Cancel  
(C) COPYRIGHT IBM CORP. 1998, 1998.

Пункт: 1. Media Analysis Report

Service Agent Media Analysis

Report Date and Time . . . . . : 24.05.08 12:29:30  
System Name . . . . . : AS/400

Type options, press Enter.  
4=Delete

Opt	Volume	Type	-----Bytes-----		-----Mounts-----	
			Read	Write	Read	Write
	FRI	6384	80B	9G	1	6
	FULL01	6384	800B	90G	10	49
	FULL02	6384	640B	69G	8	38
	FULL03	6384	640B	73G	8	41
	FULL04	6384	480B	54G	6	30
	MNTH	6384	4K	197G	26	111
	MON	6384	4K	89G	1	45
	SAT	6384	4K	89G	2	46
	THU	6384	80B	9G	1	6
	TUE	6384	5K	99G	4	51

More...

F3=Exit F6=Print report F11=Display Dates and Times F12=Cancel

[https://sysadminmosaic.ru/as\\_400/tape](https://sysadminmosaic.ru/as_400/tape)

2018-04-28 08:26

